

Zoznam súčiastok na 50Hz TVP v závislosti od použitej obrazovky.

	A59EHJ13X38	A59EAK071X11	A66EHJ13X38	A66EAK075X11	A68ELA011X101	W76ERF022X013	W76ELC021X101
C 108	CAP SNI 150UF/400V	CAP SNI 150UF/400V	CAP SNI 150UF/400V	CAP SNI 150UF/400V	CAP SNI 220UF/400V/85C	CAP SNI 220UF/400V/85C	CAP SNI 220UF/400V/85C
C 285	CAP MKP/1NF/2000V/5%	CAP MKP/1NF/2000V/5%	CAP MKP/1NF/2000V/5%	CAP MKP/1NF/2000V/5%	CAP MKP/2,2NF/2000V/5%	CAP MKP/2,2NF/2000V/5%	CAP MKP/2,2NF/2000V/5%
C 292	CAP MKP/430NF/400V/5%	CAP MKP/330NF/400V/5%	CAP MKP/430NF/400V/5%	CAP MKP/330NF/400V/5%	CAP MKP/510NF/400V/5%	CAP MKP/390NF/400V/5%	CAP MKP/390NF/400V/5%
C 352	CAP MKT/330NF/63V/20%	CAP MKT/330NF/63V/20%	CAP MKT/330NF/63V/20%	CAP MKT/330NF/63V/20%	CAP MKT/100NF/63V/5%	CAP MKT/100NF/63V/5%	CAP MKT/100NF/63V/5%
R 102	RES SQZ-10 YA 4R7 5% 10W	RES SQZ-10 YA 4R7 5% 10W	—	—	—	—	—
R 102"	—	—	RES SQZ-10 YA 4R7 5% 10W	RES SQZ-10 YA 4R7 5% 10W	RES SQZ-10 YA 4R7 5% 10W	RES SQZ-10 YA 4R7 5% 10W	RES SQZ-10 YA 4R7 5% 10W
R 252	RES CRS-100 1R5 5%	RES CRS-100 3R3 5%	RES CRS-100 1R5 5%	RES CRS-100 3R3 5%	RES MO-200 2R2 5%	RES MO-200 4R3 5%	RES MO-200 2R2 5%
R 257	RES MFS-50 39k 1%	RES MFS-50 39k 1%	RES MFS-50 39k 1%	RES MFS-50 39k 1%	RES CR-25 18K 5% /TAPE/	RES CR-25 18K 5% /TAPE/	RES CR-25 18K 5%
L 101	COIL CU15D3/1	COIL CU15D3/1	COIL CU15D3/1	COIL CU15D3/1	COIL CU20D3/7	COIL CU20D3/7	COIL CU20D3/7
T 241	FBT PET 22-37B	FBT PET 22-37B	FBT PET 22-37B	FBT PET 22-37B	FBT PET 40-11B	FBT PET 40-11B	FBT PET 40-11B
BL 301	IR RECEIVER IRM 2036	IR RECEIVER IRM 2036	IR RECEIVER IRM 2036	IR RECEIVER IRM 2036	—	—	—
HL 301	DIODE LED CSL-300 H1GT	DIODE LED CSL-300 H1GT	DIODE LED CSL-300 H1GT	DIODE LED CSL-300 H1GT	—	—	—
SA 101	POWER SWITCH KDC-A11-D221-2	POWER SWITCH KDC-A11-D221-2	POWER SWITCH KDC-A11-D221-2	POWER SWITCH KDC-A11-D221-2	—	—	—
SA 301-305	TACT SWITCH TSVD-1	TACT SWITCH TSVD-1	TACT SWITCH TSVD-1	TACT SWITCH TSVD-1	—	—	—
XP 104	—	—	2PINS M. 272802.01.02	2PINS M. 272802.01.02	2PINS M. 272802.01.02	2PINS M. 272802.01.02	2PINS M. 272802.01.02
XP 201	—	—	—	—	2PINS-M. 200102.01.51	2PINS-M. 200102.01.51	2PINS-M. 200102.01.51
XP 202	—	—	—	—	5PINS M.200105.06.51	5PINS M.200105.06.51	5PINS M.200105.06.51
XC 09	SPOJE SO ZAS. 3/40DD	SPOJE SO ZAS. 3/40DD	SPOJE SO ZAS. 3/40DD	SPOJE SO ZAS. 3/40DD	SPOJE SO ZAS. 3/40DD	—	—
XC303	SPOJE SO ZAS. 2/50DD	SPOJE SO ZAS. 2/50DD	SPOJE SO ZAS. 2/50DD	SPOJE SO ZAS. 2/50DD	SPOJE SO ZAS. 2/50DD	—	—
XC 403	CONNECTOR RS-305-06	CONNECTOR RS-305-06	CONNECTOR RS-305-06	CONNECTOR RS-305-06	CONNECTOR RS-305-06	—	—
XC 404	CONNECTOR MD-113	CONNECTOR MD-113	CONNECTOR MD-113	CONNECTOR MD-113	CONNECTOR MD-113	—	—
XT44	—	—	—	—	Spojka L = 7,87 mm	Spojka L = 7,87 mm	Spojka L = 7,87 mm
XT46	—	—	—	—	Spojka L = 7,87 mm	Spojka L = 7,87 mm	Spojka L = 7,87 mm
XT54	—	—	—	—	Spojka L = 12,5 mm	Spojka L = 12,5 mm	Spojka L = 12,5 mm
XT59	—	—	—	—	Spojka L = 12,5 mm	Spojka L = 12,5 mm	Spojka L = 12,5 mm
VN	27KV + 1KV	27KV + 1KV	27KV + 1KV	27KV + 1KV	30KV + 1KV	30KV + 1KV	30KV + 1KV