



## THE SMALL SCREEN VERTICAL DEFLECTION DRIVER

### D7231


#### DESCRIPTION

The D7231 is a monolithic integrated circuit in 4 + 4 lead minidip package. It is intended for use in black and white TV receivers and monitors and also use as class AB power amplifier with wide range of supply voltage in portable radios, cassette recorders and players, etc.


#### FEATURE

- Operating Voltage 1.8 To 15 V
- Low Quiescent Current
- High Power Capability
- Low Crossover Distortion
- Soft Clipping


Outline Drawing



#### PIN CONNECTION



#### BLOCK DIAGRAM



**ABSOLUTE MAXIMUM RATINGS (Ta=25°C)**

Characteristic	Symbol	Value	Unit
Supply Voltage	Vcc	16	V
Total Power Dissipation	Tamb=50°C	1.25	W
	Tamb=70°C	4	
Output Peak Current	Io	1	A
Storage and Junction Temperature	Tstg,Tj	-40~150	°C

**THERMAL DATA**

Characteristic	Symbol	Value	Unit
Thermal Resistance Junction-ambient	Rth j-amb	80	°C/W
Thermal Resistance Junction-pins	Rth j-pins	15	°C/W

**ELECTRICAL CHARACTERISTICS**

(Unless otherwise specified: Ta=25°C, Vcc=6V)

Characteristics	Symbol	Test conditions		Min	Typ	Max	Unit
Supply Voltage	Vcc			1.8		15	V
Quiescent Output Voltage	Vo	Vcc=6V			2.7		V
		Vcc=3V			1.2		
Quiescent Drain Current	Id			3.6	9	mA	
Input Bias Current	Ib			100		nA	
Output Sturation Voltage	Vsat1	Io=100mA			0.5		V
	Vsat2	Io=-100mA			1.0		
Distortion	THD	Po=0.2W, f=1kHz, RL=8Ω		0.3		%	
Closed Loop Voltage Gain	Gv			38		dB	
Input Resistance	Rin	f=1kHz		100		kΩ	
Total Input Noise	eN	Rs=10kΩ	B=Curve A		2		μV
			B=22Hz~22kHz		3		
Supply Voltage Rejection	SVR	Rg=10kΩ, f=100Hz		24	30		dB

### TEST CIRCUIT and APPLICATION CIRCUIT

