# **CERAMIC FILTERS**

CERAFIL® is the Registered Trademark of Murata's Ceramic Filters.




## For FM Receiver SFE10.7 Series

### **FEATURES**


- 1. These miniature filters have high mechanical strength.
- 2. Low loss, favorable waveform symmetry, and high selectivity
- 3. Various band widths are available for applications in wide to narrow bands.
- 4. Small dispersion and stable characteristics.
- 5. Change in center frequency is typically within  $\pm 30$  ppm/°C at -20 to +80℃.
- 6. High reliability.



#### DIMENSIONS



#### MEASURING CIRCUIT



#### ■SPECIFICATIONS

Part Number	3dB Band Width (kHz)	20dB Band Width (kHz) max.	Insertion Loss (dB)	Spurious Attenuation (9-12MHz) (dB) min.
SFE10.7MA5-Z	280±50	650 (520)	6 (4)	30 (43)
SFE10.7MS2-Z	230±50	600 (420)	6 (4)	40 (45)
SFE10.7MS3-Z	180±40	520 (380)	7 (4.5)	40 (45)
<ul> <li>Input/output matching impedance : 330Ω</li> </ul>				()Typ.value

)Typ.value